



BAM4

P70/P5 DIP SWITCHES SETTING : 1

Supported bill MARAKA 5(98), 10(98-1, 98-2), 20(98-1, 98-2), 50(98-1, 98-2) 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MARAKA 5	OFF	OFF	OFF							
	2 Pulse / MARAKA 5	OFF	OFF	ON							
	3 Pulse / MARAKA 5	OFF	ON	OFF							
	4 Pulse / MARAKA 5	OFF	ON	ON							
	5 Pulse / MARAKA 5	ON	OFF	OFF							
	10 Pulse / MARAKA 5	ON	OFF	ON							
	20 Pulse / MARAKA 5	ON	ON	OFF							
	100 Pulse / MARAKA 5	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept MARAKA 5				ON						
	Reject MARAKA 5				OFF						
★	Accept MARAKA 10				ON						
	Reject MARAKA 10				OFF						
★	Accept MARAKA 20				ON						
	Reject MARAKA 20				OFF						
★	Accept MARAKA 50				ON						
	Reject MARAKA 50				OFF						
	HOLD				ON						
					OFF						

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	Pulse Protocol	ON			
	ICT Protocol	OFF			
	HOLD			ON	
				OFF	
	Ignore Sensor Problem(Note 1)				ON
★	Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)

