



BRA6

P70/P5 DIP SWITCHES SETTING : 1

Supported bill R\$ 1(94, 03), 2(01), 5(94), 10(94, 00),
20(02), 50(94) 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / R\$ 1	OFF	OFF								
2 Pulse / R\$ 1	OFF	ON								
4 Pulse / R\$ 1	ON	OFF								
10 Pulse / R\$ 1	ON	ON								
★ Output Pulse Lo= 50ms Hi=100ms			OFF	OFF						
Output Pulse Lo=150ms Hi=100ms			OFF	ON						
Output Pulse Lo= 20ms Hi=100ms			ON	OFF						
Output Pulse Lo= 30ms Hi=150ms			ON	ON						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept R\$ 1						ON				
Reject R\$ 1						OFF				
★ Accept R\$ 2							ON			
Reject R\$ 2							OFF			
★ Accept R\$ 5								ON		
Reject R\$ 5								OFF		
★ Accept R\$ 10									ON	
Reject R\$ 10									OFF	
★ Accept R\$ 20 & 50										ON
Reject R\$ 20 & 50										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
Pulse Protocol		ON		
ICT Protocol		OFF		
HOLD			ON	
			OFF	
				ON
				OFF

