



# CLP4

## P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Ch\$ 1000, 2000, 5000, 10000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Ch\$ 1000	OFF	OFF	OFF							
	2 Pulse / Ch\$ 1000	OFF	OFF	ON							
	3 Pulse / Ch\$ 1000	OFF	ON	OFF							
	4 Pulse / Ch\$ 1000	OFF	ON	ON							
	5 Pulse / Ch\$ 1000	ON	OFF	OFF							
	10 Pulse / Ch\$ 1000	ON	OFF	ON							
	20 Pulse / Ch\$ 1000	ON	ON	OFF							
	100 Pulse / Ch\$ 1000	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Ch\$ 1000				ON						
	Reject Ch\$ 1000				OFF						
★	Accept Ch\$ 2000				ON						
	Reject Ch\$ 2000				OFF						
★	Accept Ch\$ 5000				ON						
	Reject Ch\$ 5000				OFF						
★	Accept Ch\$ 10000				ON						
	Reject Ch\$ 10000				OFF						
★	Reserved				ON						
					OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

